

Pair Bluetooth Controllers - manual setup

You need to establish a [SSH connection](#) or a terminal windows with keyboard to accomplish this further. You can connect your bluetooth controller manually by doing some commands step by step.

Get started by typing `bluetoothctl` and hitting [Enter].

Now you are in the Bluetooth control unit. Type following commands and confirm every single one with [Enter]

```
agent on
default-agent
power on
scan on
```

Now set the controller in pairing mode! This strongly depends from your [controller type](#).

An example of the output you would see from running all the commands successfully:

```
[root@BATOCERA /userdata/system]# bluetoothctl
Agent registered
[bluetooth]# agent on
Agent is already registered
[bluetooth]# default-agent
Default agent request successful
[bluetooth]# power on
Changing power on succeeded
[bluetooth]# scan on
Discovery started
[CHG] Controller 43:45:C0:00:1F:AC Discovering: yes
[NEW] Device E4:17:D8:C2:0B:0E 8BitDo M30 Modkit
```



If you're having trouble detecting devices, check out the [Bluetooth section on the troubleshooting page](#).

Now we want to connect to our controller. So we type following commands to connect to discovered controller with MAC address `E4:17:D8:C2:0B:0E` properly. Wait a few seconds after entering the commands in order to ensure they are processed successfully.

```
pair E4:17:D8:C2:0B:0E
connect E4:17:D8:C2:0B:0E
trust E4:17:D8:C2:0B:0E
```

This would be the output from our example:

```
[bluetooth]# pair E4:17:D8:C2:0B:0E
```

```
Attempting to pair with E4:17:D8:C2:0B:0E
[CHG] Device E4:17:D8:C2:0B:0E Connected: yes
[CHG] Device E4:17:D8:C2:0B:0E Modalias: usb:v2DC8p5101d0100
[CHG] Device E4:17:D8:C2:0B:0E UUIDs: 00001124-0000-1000-8000-00805f9b34fb
[CHG] Device E4:17:D8:C2:0B:0E UUIDs: 00001200-0000-1000-8000-00805f9b34fb
[CHG] Device E4:17:D8:C2:0B:0E ServicesResolved: yes
[CHG] Device E4:17:D8:C2:0B:0E Paired: yes
Pairing successful

[bluetooth]# connect E4:17:D8:C2:0B:0E
Attempting to connect to E4:17:D8:C2:0B:0E
Failed to connect: org.bluez.Error.Failed
[CHG] Device E4:17:D8:C2:0B:0E Connected: yes
Authorize service (yes/no): yes

Authorize service 00001124-0000-1000-8000-00805f9b34fb
[8BitDo M30 Modkit]# trust E4:17:D8:C2:0B:0E
[CHG] Device E4:17:D8:C2:0B:0E Trusted: yes
Changing E4:17:D8:C2:0B:0E trust succeeded
```

Type devices to see a list of devices configured in your BT setup.
Type remove MAC-ADRESS to remove single devices
Type yes if you are asked for authorization progress or enter PIN

If you have multiple Bluetooth adapters on your machine and you want to tell which one is used, you can use the command `hcitool dev` to list them all. On my setup, `hci0` is the internal BT on my Pi4, and `hci1` is an additional USB BT module:

```
# hcitool dev
Devices:
    hci1    90:80:62:00:88:00
    hci0    DC:A6:32:04:10:7F
# bluetoothctl
Agent registered
[bluetooth]# scan on
Discovery started
[CHG] Controller 90:80:62:00:88:00 Discovering: yes
```

From:
<https://wiki.batocera.org/> - **Batocera.linux** - Wiki

Permanent link:
https://wiki.batocera.org/bluetooth_controllers_-_manual_setup?rev=1633503833

Last update: **2021/10/06 07:03**

