

Sega NAOMI

The Sega NAOMI (stands for "New Arcade Operation Machine Idea") is a arcade developed by Sega. It was released in 1998. Designed to be the successor to the [Model 3](#), it uses similar architecture to that of the [Dreamcast](#). Because of this, emulation of NAOMI games is usually best done with a Dreamcast emulator (modifications have already been made to allow for this in Flycast, for instance). Features arcade games like Crazy Taxi, Dead or Alive 2 and Samba de Amigo.



Although "NAOMI" can refer to multiple different types of boards released by Sega during this time period, Batocera specifically refers to just the original NAOMI board released in 1998 when mentioning "NAOMI" (at least for now).

Due to the similarity between NAOMI and the Dreamcast, most games were also ported to the Dreamcast, and a few even getting ported to other consoles of the generation. It may be easier to attempt to emulate those than their arcade counterparts.

For those interested in the hardware aspect, [here's a cool article about it on Sega Retro](#).

This system scrapes metadata for the "naomi" and "arcade" groups and loads the naomi set from the currently selected theme, if available.

Quick reference

- **Accepted ROM formats:** .lst, .bin, .dat, .zip, .7z
- **Folder:** /userdata/roms/naomi

Emulators
libretro: Flycast
Flycast

BIOS

The BIOS is optional but I dunno you probably want to include it anyway.

MD5 checksum	Share file path	Description
eb4099aeb42ef089cfe94f8fe95e51f6	bios/naomi.zip	NAOMI MAME BIOS

Some games have optional extra BIOS files that can be used, but they aren't required to run them.

MD5 checksum	Share file path	Description
	hod2bios.zip	The House of the Dead 2 MAME BIOS
	f355dlx.zip	Ferrari F355 Challenge Deluxe MAME BIOS
	f355bios.zip	Ferrari F355 Challenge Twin/Deluxe MAME BIOS
	airlbios.zip	Airline Pilots Deluxe MAME BIOS

ROMs

Place your Sega NAOMI ROMs in /userdata/roms/naomi.

[User-friendly compatibility list for Flycast.](#)

If you're willing to search through code, [here's the list of all the expected ROM hashes.](#)

Some NAOMI boards use just ZIP ROMs to run, but most others use a ZIP in addition to an image (or [CHD](#)) file. In order to use ROMs that come with a image, the image must be placed in a subfolder with the same name as the game's ZIP file with the MAME ID as its filename. For example:

```
roms/
└─ naomi/
   └─ ikaruga/
      └─ gdl-0010.chd
      └─ ikaruga.zip
```

Emulators

RetroArch

[RetroArch](#) (formerly SSNES), is a ubiquitous frontend that can run multiple “cores”, which are essentially the emulators themselves. The most common cores use the [libretro](#) API, so that's why cores run in RetroArch in Batocera are referred to as “libretro: (core name)”. RetroArch aims to unify the feature set of all libretro cores and offer a universal, familiar interface independent of platform.

RetroArch configuration

RetroArch offers a **Quick Menu** accessed by pressing [HOTKEY] +  which can be used to alter various things like [RetroArch and core options](#), and [controller mapping](#). Most RetroArch related settings can be altered from Batocera's EmulationStation.

Standardized features available to all libretro cores: naomi.videomode, naomi.ratio, naomi.smooth, naomi.shaders, naomi.pixel_perfect, naomi.decoration, naomi.game_translation

ES setting name batocera.conf_key	Description ⇒ ES option key_value
Settings that apply to all cores of this emulator	

ES setting name batocera.conf_key	Description ⇒ ES option key_value
GRAPHICS BACKEND naomi.gfxbackend	Choose your graphics rendering ⇒ OpenGL opengl, Vulkan vulkan.
AUDIO LATENCY naomi.audio_latency	Audio latency in milliseconds, turn it up if you hear crackles ⇒ 256 256, 192 192, 128 128, 64 64, 32 32, 16 16, 8 8.
THREADED VIDEO naomi.video_threaded	Improves performance at the cost of latency and more video stuttering. Use only if full speed cannot be obtained otherwise. ⇒ On true, Off false.

libretro: Flycast

A fork of a fork of a fork... this is an identical version of standalone Flycast but inside of a libretro core. Makes use of RetroArch's features.

libretro: Flycast configuration

ES setting name batocera.conf_key	Description ⇒ ES option key_value
Settings that apply to all systems this core supports	
SYNCHRONOUS RENDERING global.reicast_synchronous_rendering	Wait for the GPU to render frames instead of skipping ⇒ Off disabled, On enabled.
VIDEO RESOLUTION global.reicast_internal_resolution	Improve the fidelity of 3D models (does not affect 2D sprites) ⇒ 640×480 640×480, 800×600 800×600, 960×720 960×720, 1024×768 1024×768, 1280×960 1280×960, 1440×1080 1440×1080, 1600×1200 1600×1200, 1920×1440 1920×1440, 2560×1920 2560×1920, 3200×2400 3200×2400, 3840×2880 3840×2880, 4480×3360 4480×3360, 5120×3840 5120×3840, 5760×4320 5760×4320, 6400×4800 6400×4800, 7040×5280 7040×5280, 7680×5760 7680×5760.
TEXTURE MIP-MAPPING (BLUR) global.reicast_mipmapping	Smooths out textures on 3D objects ⇒ Off disabled, On enabled.

ES setting name batocera.conf_key	Description ⇒ ES option key_value
ANISOTROPIC FILTERING global.reicast_anisotropic_filtering	Enhance the quality of distant perspective textures ⇒ Off False, 2x 2, 4x 4, 8x 8, 16x 16.
TEXTURE UPSCALING (XBRZ) global.reicast_texupscale	Upscaling 2D pixel art graphics (2D Games Only) ⇒ Off False, 2x 2x, 4x 4x, 6x 6x.
RENDER TO TEXTURE UPSCALING global.reicast_render_to_texture_upscaling	Upscaling textures resolution on 3D objects ⇒ Off 1x, 2x 2x, 3x 3x, 4x 4x, 8x 8x.
FRAME SKIP global.reicast_frame_skipping	Skip frames to improve performance (smoothness) ⇒ Off disabled, 1 1, 2 2, 3 3, 4 4, 5 5, 6 6.
FORCE WINDOWS CE MODE global.reicast_force_wince	Enable full MMU emulation for Windows CE games ⇒ Off disabled, On enabled.
WIDESCREEN CHEAT (PRIORITY) global.reicast_widescreen_cheats	You must use a 16/9 RATIO and disable BEZEL ⇒ Off disabled, On enabled.
WIDESCREEN HACK global.reicast_widescreen_hack	You must use a 16/9 RATIO and disable BEZEL ⇒ Off disabled, On enabled.
CONTROLLER 1 TYPE global.controller1_dc	Select Gamepad, Keyboard, Mouse or Light Gun ⇒ Gamepad 1, Keyboard 3, Mouse 2, Light Gun 4.
CONTROLLER 2 TYPE global.controller2_dc	Select Gamepad, Keyboard, Mouse or Light Gun ⇒ Gamepad 1, Keyboard 3, Mouse 2, Light Gun 4.
CONTROLLER 3 TYPE global.controller3_dc	Select Gamepad, Keyboard, Mouse or Light Gun ⇒ Gamepad 1, Keyboard 3, Mouse 2, Light Gun 4.
CONTROLLER 4 TYPE global.controller4_dc	Select Gamepad, Keyboard, Mouse or Light Gun ⇒ Gamepad 1, Keyboard 3, Mouse 2, Light Gun 4.
Settings specific to atomiswave	
SCREEN ORIENTATION atomiswave.screen_rotation_atomiswave	Rotate screen for some arcade games ⇒ Horizontal horizontal, Vertical vertical.
Settings specific to naomi	

ES setting name batocera.conf_key	Description ⇒ ES option key_value
SCREEN ORIENTATION naomi.screen_rotation_naomi	Rotate screen for some arcade games ⇒ Horizontal horizontal, Vertical vertical.

All other settings can be configured from RetroArch's **Quick Menu** → **Options** ([H0TKEY] + ).

Flycast

[Flycast](#) is a fork of [Reicast](#) (which itself is a fork of nullDC). A highly compatible and accurate standalone Dreamcast emulator.

Flycast can also be used to run NAOMI arcade games due to being nearly identical hardware. Not all NAOMI games are [compatible](#) yet but most of them are.

Flycast configuration

Standardized features available to all cores of this emulator: `naomi.videomode`, `naomi.ratio`

Flycast cannot be configured in EmulationStation; all other configuration must be done via the `flycast-config` in the Applications folder ([F1] on the systems screen).

Controls

 How does this even work?


Here are the default Sega Naomi's controls shown on a [Batocera Retropad](#):



Troubleshooting

Further troubleshooting

For further troubleshooting, refer to the [generic support pages](#).



From:

<https://wiki.batocera.org/> - **Batocera.linux** - Wiki

Permanent link:

<https://wiki.batocera.org/systems:naomi?rev=1638431240>

Last update: **2021/12/02 07:47**

